

PS40

6" 30W Portable PA System with Battery



Features

• Controls

- 30W Rated Power output.
- 2 Mic / Line input and 1 Line input.
- 2 Band master EQ and Volume for each input channels
- 1 Effect volume

• Input Connectors

- XLR & 1/4" phone jack for Mono input.
- 1/4" Phone jack & 3.25mm Phone jack or Phono jack for Line input.

• Indicator

- Power on, Battery Charge LED.
- Handle easy carrying.

Specifications

		PS40
Rated Power @ THD 1%		30W
Input Sensitivity / Impedance	Mic	2mV/20Kohm Balanced
	Line	150mV/10Kohm Unbalanced
Frequency Response		35Hz to 16KHz
THD @1/3 Rated Power		0.1%
Signal to Noise Ratio	Mic	65dB
	Line	80dB
Master Equalization		High: 10KHz 10dB, Low: 100Hz 10dB
Effect		Echo for Mic Input
AMP		Class D
Power Supply		12V / 2.6AH Battery 19V / 3A Adapter
Speaker	LF	6"
	HF	1"
	X-over Frequency	3.5KHz
Power Source		100V-240V, 50/60Hz
Weight (Net)		5.72 kg
Dimensions (W x H x D)		218 x 348 x 200mm